

12153RRUS01U

USE OF TRELLIS CODED MODULATION TO MITIGATE
FADING CHANNELS IN DATA TRANSMISSION OVER
AIR LINK WIRELESS CHANNELS OF GPRS/EDGE SYSTEMS

BACKGROUND OF THE INVENTION

5 1. Field of the Invention:

10 The present invention relates in general to wireless communications and in particular to a system and method for transmitting data over a wireless channel. Still more particular, the present invention relates to a system and method for providing greater capacity and reduced fading channel effects with transmission of data over a wireless channel of GPRS or EDGE systems.

2. Description of the Related Art:

15 Wireless communication utilizes various defined standards for voice and data communications. Universally accepted standards are General Packet Radio Services (GPRS), a packet-based wireless communication service that provides data rates from 56 up to 114 Kbps and continuous connection to the Internet for mobile phone and computer users, and Enhanced Data GSM Environment (EDGE), a faster version of the Global System for Mobile (GSM) wireless service that is designed to deliver data at rates up to 384 Kbps and enable the delivery of multimedia and other broadband applications to mobile
20 phone and computer users.
25

 The EDGE standard is built on the existing GSM standard, using the same time-division multiple access

12153RRUS01U

(TDMS) frame structure and existing cell arrangements.
EDGE is designed to provide Universal Mobile Tele-
communications Service (UMTS).

5 GPRS offers higher data rates than traditional
standards and allows users to take part in video
conferences and interact with multimedia Web sites and
similar applications using mobile hand-held devices as
well as notebook computers. GPRS is also based on GSM
communication and complements existing services such as
10 circuit-switched cellular phone connections and the Short
Message Service (SMS). A more in-depth presentation of
GSM may be found in Michel Mouly and Marie-Bernadette
Pautet: *GSM System for Mobile Communications*, 1992.

15 During the initial implementations, wireless
telephony was used only for voice communications. Voice
recognition is robust to bit error rate, i.e., the human
ear is insensitive to most bit error rate found in a
typical wireless voice transmission. Thus, these voice-
communication systems are typically configured with
20 convolution-based modulation over the air link.

There is a growing desire to be able to efficiently
transfer data over the wireless air link as provided with
the traditional voice-based wireless transmission
systems. Data transmission systems have been designed
25 that utilize the convolution-based modulation. These
systems exhibit inherent limitations when attempting to
transfer data over the wireless link primarily due to the
significant bit error rates due to fading channel
phenomena in wireless air link transmission.

30 Unlike voice communication, data communication does
not tolerate errors in transmission. Thus, the GRPS
system, which utilizes convolutional coding, though

09738755 134500

12153RRUS01U

capable of transmitting data at relatively high speeds,
is limited by the bit error rate. Spread spectrum in
CDMA has been suggested to overcome some of the
limitations of convolutional coding, but spread spectrum
5 leads to significant signal interference and does not
address the fading channel problem. Also, while the
wireless air link bandwidth is limited by industry-
allocated spectrum, there is an ever-increasing demand
for bandwidth in wireless data communications in GPRS and
10 EDGE.

The present invention recognizes that a method and
system that provides both higher capacity and errorless
transmission of data over a wireless air link would be
desired. The present invention further recognizes that a
15 significant advantage can be achieved by providing better
encoding/decoding that substantially eliminates fading
channel effects for data being transmitted in GPRS/EDGE
systems.

12153RRUS01U

SUMMARY OF THE INVENTION

Disclosed is a system and method for improving efficiency and overall capacity of data transmission within a given bandwidth in a GPRS/EDGE wireless air-link channel. A GPRS data terminal, mobile unit and/or other end-user equipment is equipped with a (specially designed) Trellis coder that replaces the traditional convolutional coder and allows encoding and decoding of data via the Trellis code algorithm. Trellis coder eliminates errors in data transmission or increases the data rate over a given bandwidth for the same error rate. The Trellis coder is also utilized for voice transmission and may be fabricated on an integrated circuit for utilization within hand-held devices.

The above as well as additional objects, features, and advantages of the present invention will become apparent in the following detailed written description.

12153RRUS01U

BRIEF DESCRIPTION OF THE DRAWINGS

The novel features believed characteristic of the invention are set forth in the appended claims. The invention itself however, as well as a preferred mode of use, further objects and advantages thereof, will best be understood by reference to the following detailed description of an illustrative embodiment when read in conjunction with the accompanying drawings, wherein:

Figure 1 is a block diagram of a GPRS network utilized within a preferred embodiment of the invention;

Figures 2A-2C are a series of block diagrams illustrating frame hierarchy for traffic channels according to one embodiment of the invention;

Figure 3 is a block diagram illustrating a sequence of operations for converting speech/data to radio wave for wireless transmission in accordance with one embodiment of the invention;

Figures 4A and 4B illustrate a basic convolutional encoder and the corresponding Trellis diagram, respectively in accordance with one embodiment of the invention;

Figure 5 is a comparative diagram illustrating an un-coded pulse amplitude modulation model and a Trellis coding model for data transmission with the same average signaling power in accordance with one implementation of the invention;

5

Figures 7 and 8 illustrate block diagram representations of an encoder/decoder pair utilized in one preferred embodiment of the invention.

12153RRUS01U

DETAILED DESCRIPTION OF AN ILLUSTRATIVE EMBODIMENT

With reference now to the figures and in particular with reference to **Figure 1**, there is illustrated a general diagram of the topology of a GPRS network 10 utilized to implement a preferred embodiment of the invention. The GPRS network 10 comprises a mobile switching center (MSC)/visitor location register (VLR) 12, a home location register (HLR) and authentication center (AuC) 14, a gateway GPRS support node (GGSN) 20, a serving GPRS support node (SGSN) 24, and a base station system (BSS)/packet control unit (PCU) 28. BSS has an associated BSS antenna 30, which provides a wireless airlink with mobile terminal 27 via mobile terminal antenna 29. The MSC/VLR 12 provides voice communications for wireless (cellular) terminals. The MSC/VLR 12 is in direct communications with the HLR/AuC 14, the SGSN 24, and the BSS/PCU 28. The HLR/AuC 14 is in direct communications with SGSN 24 and GGSN 20.

The GPRS network 10 is configured to support interfaces to and from packet data networks. **Figure 1** shows that the GGSN 20 is coupled to, and in communications with, outside packet data networks that support the Internet Protocol (IP) 16 or the X.25 protocol 18. In **Figure 1**, data packets come in from the outside network (i.e. IP 16 or X.25 networks 18) to the GGSN 20, then to the SGSN 24, and then to the BSS/PCU 28. Thus, two-way communications exist between the BSS/PCU 28 and the SGSN 24, the GGSN 20, and the outside network(s).

12153RRUS01U

0973859400

Figures 2A-2C, illustrates a 120 msec multi-frame **201**, which consists of 26 slots **203** (i.e., time division multiple access (TDMA) frames). Of the 26 slots **203** in the 120 msec multi-frame **201**, 25 are used for voice, while 1 is used for signaling. Each slot **203** consists of 8 Burst Periods (BPs) **205** each of 577 mksec duration. One BP **205** within the slot corresponds to one transmission channel (TCH). Because each TCH supports a single conversation in operation, one TCH slot **203** can simultaneously carry 8 conversations.

Figure 3 illustrates the process (or sequence of operations) required in the conversion of speech or analog signal **301** to radio wave or digital signal (i.e., BP bits) **313**, which may then be transmitted via a wireless air link. As represented by the various blocks, several steps are required to complete the process. These steps include channel coding **303**, interleaving **305**, burst formatting **307**, ciphering **309**, and modulation **311**. The sequence of steps is also utilized when converting data to digital signals **313**. A reversed set of steps is utilized to convert received digital signals into their corresponding analog counterparts.

The invention is primarily implemented within the block designated for channel-coding **303**. In the preferred embodiment, the function of channel-coding **303** during forward signal transmission is provided by a Trellis channel-encoder block that is specially designed to provide the improvements of the present invention as further described below. Conversely, during signal reception, function of channel-coding **303** is provided by

12153RRUS01U

a corresponding specially designed Trellis channel-decoder.

5 The preferred embodiment of the present invention
thus provides a Packet Data Traffic Channel (PDTCH) that
utilizes TCM coders to perform channel-coding 313. The
invention thus provides a hardware and/or logic system at
a data station by which channel coding at the origination
station is completed by a TCM encoder and channel
10 decoding at the receiving data station is completed by a
TCM decoder. Although described herein as separate
components, the invention contemplates utilizing a single
encoder/decoder device to perform channel-coding 303.

15 The preferred embodiment of the invention, as
described herein, focuses primarily on Traffic Channel
(TCH)/Full Rate (F) (i.e., TCH/F not TCH half rate). The
invention provides data accuracy for data traffic, while
transmitting data at the highest possible speed and/or
capacity by utilizing Trellis Coding over the air link
20 channel PDTCH. Utilization of Trellis Coded Modulation
(TCM) significantly expands the data rate within the same
available bandwidth. In standard implementation, the
data's bit rate is increased at the cost of greater
encoder and decoder complexities; however, the additional
25 complexities of both components can be afforded, and the
TCM coders are easily incorporated within the wireless
data terminals.

30 In the preferred embodiment, the TCM is placed on
top of Quadrature Amplitude Modulation (QAM) which is
utilized in the coding sequence. TCM enables robust
error immunity for data with significantly increased data
rate over the data rates of the methods presently being
utilized.

12153RRUS01U

Voice transmissions by mobile phones are not adversely affected by the present coding systems because the bit errors in voice transmission can be tolerated. However, the present invention contemplates also
5 extending the features associated with TCH coding to voice transmission over hand-held mobile units (e.g., mobile phones) to allow for additional capacity for wireless voice communications. Utilization of TCM for
10 simultaneous voice conversation within the available bandwidth. Continuing developments in Integrated Circuits (IC) technology allows for the miniaturization of the Trellis encoder and decoder components to allow
15 to be incorporated within a mobile phone without necessarily increasing the phone or other small, wireless components.

Figures 4A and 4B illustrate a simple Trellis Coding example. Trellis Coding is a special case of
20 convolutional coding where coded words are allocated to the signals to obtain the maximum Euclidian distance between "neighboring" words for limited signal power. Obtaining the maximum Euclidian distance increases data rates significantly over the same physical channel and
25 with the same accuracy. In the preferred embodiment, Trellis coding employs Amplitude Phase modulation and thus forms different constellation lattices in the signaling space.

Referring to **Figure 4A**, a Rate 2/3 convolutional
30 encoder is illustrated. For the illustrated example, an assumption is made that the convolutional encoder has shift register size $K=3$. For every pair of input bits the encoder **401** produces 3 output bits **403**. The encoder

12153RRUS01U

has 4 states and the corresponding Trellis diagram is shown in **Figure 4B**.

Figure 4B illustrates the Trellis diagram **411** for the encoder **401** of **Figure 4A**. Trellis coding associates vector signals **413** associated with input states **415** in such a way that Trellis coincidence signals have the maximum Euclidian distance.

Figure 5 illustrates results of both the un-coded pulse amplitude modulation (PAM) **503** and Trellis coded modulation **501** and corresponding Euclidian distances for the same average signaling power according to **Figure 4B**. From **Figure 5**, the average signaling power is calculated as:

$$S_a = \sum d_i^2 / M,$$

where d is the distance from origin or signaling amplitude yielding d^2 as the signaling power, and M is the number of signals. As calculated, $S_a = 21$ in both the un-coded PAM **503** and Trellis coding **501**. The immunity to the noise of both coding schemes with the same power may be compared by the minimum Euclidian distance between code words. With the un-coded PAM model **503**, the minimum distance is: $(6.15 - 2.05)^2 = 16.8$. With Trellis coding **501**, the minimum distance is: $(7-3)^2 + (7-5)^2 + (7-3)^2 = 36$.

Therefore, the distance-to-power ratio for the Trellis coding **501** is $36/21 = 1.71$, while that for the un-coded PAM **503** is $16.8/21 = 0.8$. The difference is a

12153RRUS01U

factor of 2.14 times worst for the un-coded PAM 503. The Trellis gain in dB is calculated as:

$$10 \cdot \log(\text{Trellis}/\text{un-coded}) = 3.3 \text{ dB}.$$

As indicated, use of Trellis Coding in GPRS and EDGE increases possible data rate by several order of magnitude. For example, if GPRS maximum data rate with current method is 200kbps, TCM coding may increase the data rate to over 1 mbps. TCM coding thus enables almost full usage of Shannon's channel capacity, and TCM with QAM enables maximum bit rate for a given bandwidth.

An analysis of design considerations to overcome channel fading in a Trellis coder is provided below. Application of the results of the analysis to actual coder/decoder decisions is provided in **Appendix A**.

Fading channels present a different problem when designing the Trellis systems described above. To calculate the fading channel effects, the upper bound on P_b average bit error probability is defined as

$$P_b \leq \sum_{x \in \zeta} \sum_{\hat{x} \in \zeta} a(x, \hat{x}) p(x) P(x \rightarrow \hat{x}),$$

where $a(x, \hat{x})$ is the number of bit errors that occur when the sequence x is a transmitted sequence and $\hat{x} \neq x$ is chosen by the decoder, $p(x)$ is the a-priori probability of transmitting x with ζ the set of coded sequences and finally $P(x \rightarrow \hat{x})$ is the pairwise error probability. For the Rayleigh fading channel, the important term in the equation is more specifically defined as

$$P(x \rightarrow \hat{x}) \leq \left(\prod_{n \in \eta} \frac{\bar{E}_s}{4N_0} |x_n - \hat{x}_n|^2 \right)^{-1},$$

12153RRUS01U

where $x = [x_1, x_2, x_3, \dots, x_n, \dots, x_N]$, $\hat{x} = [\hat{x}_1, \hat{x}_2, \hat{x}_3, \dots, \hat{x}_n, \dots, \hat{x}_N]$ are vectors with N components and $x_n \neq \hat{x}_n$ is the set η . The signal-to-noise ratio is $\frac{\bar{E}_s}{N_0}$

5 A more general form of the equation for Rayleigh or Rician fading channels is

$$P(x \rightarrow \hat{x}) \leq \left(\prod_{n \in \eta} \frac{(1+K)}{\left(\frac{\bar{E}_s}{4N_0} \right) |x_n - \hat{x}_n|^2} e^{-K} \right), 0 \leq K \leq \infty,$$

where K is the Rician coefficient.

10 The Trellis design rule for a Rayleigh or Rician fading channels is to maximize the number of symbols with non-zero Euclidean distance along the error event path of shortest length. With the above design rules, the following design guidelines are established and utilized by the present invention in designing the associated Trellis coders for the air link wireless channels.

15 First, for any 1-D TCM design the number of parallel branches must be minimized, and second, Multidimensional TCM designs allow multiple symbols per Trellis branch, thus parallel branches can result in diversity gain as long as there are enough differences in the symbols per

20 branch

With multidimensional TCM schemes, there are different methods to increase n in the above equation. One approach, the Trellis-coded multidimensional phase modulation, uses higher dimensional forms of simple

25 constellations (e.g. QPSK, MPSK) to form new

12153RRUS01U

constellations (e.g. L XQPSK, L XMPSK). Multiple TCM (MTCM) is another technique that uses higher dimensional forms of simpler constituent constellations. MTCM provides fading channel diversity gain by providing a set partitioning technique that maximizes the number of symbol difference per partition subset. In the preferred embodiment, Trellis-coded multidimensional phase modulation uses a simpler set partitioning method procedure that doesn't necessarily yield the large symbol differences with a sub-set but does yield higher rate codes, thus preserving higher user data rates.

Another approach that increases n is to increase the dimensionality of constellation and use simple constellations (e.g. BPSK) for transmission over the channel. For example, a Gosset lattice is an 8-dimensional lattice that uses constituent Reed-Muller to construct constellation points to transmit over a channel. The Leech lattice is a 24 dimensional lattice that also uses BPSK to transmit code words over the channel. Further diversity gain is achieved by using multidimensional extensions of the same lattices. However, these techniques might not achieve the same bandwidth efficiency gains of higher order modulations but do achieve diversity gain to mitigate fading.

With the above analysis, the present invention thus utilizes a specific approach in designing Trellis coders to reduce fading within transmission channels while providing increased data transmission capacity. The approach utilized by the invention includes the utilization of higher dimensional lattices over simpler modulation schemes or existing modulation schemes, which minimizes the impact to the structure of the modulation for current standards (e.g., GPRS uses GMSK and/or QPSK modulation). The implementation provides burst error

12153RRUS01U

correction like Reed-Solomon codes with the 2 dB added benefit of soft-decision decoding via Viterbi decoders. The approach also provides higher rate codes and consequently preserves user data rates.

5 The approach also includes the utilization of higher dimensional lattices constructed from Reed-Muller codes to exploit the inherent implementation simplicity of these codes, and/or Utilization of multidimensional variants of these higher dimensional lattices (i.e.
10 constellations) to get further diversity gain on the fading channel. A predetermined set partitioning scheme is utilized along with the codeword partitioning scheme to form sub-set partitions. The set partitioning scheme is further described in S. S. Pietrobon, R. H. Deng, A.
15 Lafanechere, G. Ungerboeck and D. J. Costello, Jr., "Trellis-Coded Multidimensional Phase Modulation", *IEEE Transactions on Information Theory*, vol. 36, No. 1, January 1990, the content of which is hereby incorporated by reference.

20 The approach utilized further comprises utilization of exhaustive searching to find the sub-set partitions with the largest symbol difference within a partition. Thus higher diversity gain is achieved along parallel branches as per MTCM. Finally, utilization of fractional
25 dimensional Reed-Muller codes to construct code rates beyond the standard Reed-Muller codes is made and fractional dimensional codes are built to match user data rate requirements.

30 The design parameters above are utilized to produce several different implementations of Trellis coders as further described in **Appendix A**, which further describes how the Trellis-coded multidimensional Reed-Muller codes can be applied for the Gosset lattice (E_8).

12153RRUS01U

Figure 6 is a block diagram illustrating the general structure of an encoder, which may be advantageously utilized within a data terminal of a wireless air link GPRS system in one embodiment of the invention. As illustrated, encoder **601** comprises several functional blocks, including a differential precoder **603**, a rate $R=k/(k+1)$ convolutional encoder **605**, a multidimensional signal set mapper **607**, and a Reed-Muller signal set mapper **609**. The differential precoder **603** preserves rotational invariance of signal sets, and the rate $R=k/(k+1)$ convolutional encoder **605** provides redundancy in signal space.

Figures 7 and 8 are block diagrams illustrating a Trellis encoder/decoder pair utilized in one preferred embodiment of the invention. The design of the encoding stage is driven by a set of parameters needed to compute bit-error-rate (BER) performance. Encoder **701** has $k=5$ input bits **703** (i.e., b_1, b_2, \dots, b_5) and 8 output bits **705** (i.e., two 4 bit code words). There are 3 memory elements **707** (i.e. $v=3$) which generate 3 additional bits **704** (i.e., b_6, b_7, b_8) to the non-linear mapping function. The non-linear mapping function **709** uses the bits b_1, b_2, \dots, b_8 **703 704** to form code words formed by the trellis branches of a multidimensional design. Specific parameters related to the encoder/decoder pair are also provided in **Appendix A**.

Figure 8 shows the decoder **801** for the 2-D (4,3) Reed-Muller code. Input message bits **803** with $u_i(t)=[b_1(t), b_2(t), \dots, b_5(t)]$ are encoded by 2-D encoder **804** into code word 2-tuples $c(t)=[y_1(t), y_2(t)]^T$ **805** where

12153RRUS01U

each $y_1(t), y_2(t)$ is a (4,3) Reed-Muller code word. These code words are modulated and transmitted over an AWGN channel with noise $n(t)$ to Trellis decoder 811. The Viterbi decoder 809 receives channel signal $r(t)$ 807 and forms estimates of channel code words (t) 813 and stores accompanying state progression information in a Trellis. Following, code words (t) 813 are passed through inverse non-linear mapping 815 to produce output 817.

A more detailed analysis of Trellis Coding and types or models of Trellis Coders (encoders/decoders) and their specific implementations, which may advantageously be utilized in the implementation of the present invention may be found in **Appendix A**, the entire content of which is hereby incorporated by reference.

It is important to note that while the present invention has been described in the context of a fully functional data processing system, those skilled in the art will appreciate that certain elements of the method of the present invention are capable of being distributed in the form of a computer readable medium of instructions in a variety of forms, and that the present invention applies equally, regardless of the particular type of signal bearing media utilized to actually carry out the distribution. Examples of computer readable media include: nonvolatile, hard-coded type media such as Read Only Memories (ROMs) or Erasable, Electrically Programmable Read Only Memories (EEPROMs), recordable type media such as floppy disks, hard disk drives and CD-ROMs, and transmission type media such as digital and analog communication links.

While the invention has been particularly shown and described with reference to a preferred embodiment, it

2021

2021